



Din Rail Mount AC Power Supplies

PSD

Description:

The PSD Power Supplies are designed for Applications where a low current AC Supply is required such as valves and Damper actuators.



Features:

- ◆ Din rail mounting.
- ◆ Compact.
- ◆ Fused Primary and Secondary .
- ◆ 240Vac Primary, 24Vac Secondary
- ◆ 1.5VA, 6VA and 15VA Versions.

Technical Specification:

Output:	24Vac	
Supply Voltage:	230Vac	
Current ratings:	1.5VA, 6VA and 15VA	
Termination:	Rising Clamp for 0.5 to 2.5mm ² Cable.	
Fuse rating:	1.5VA	100mA
	6VA	250mA
	15VA	630mA
Dimensions:		
1.5VA	47mm(W)x55mm(D)x93mm(H)	
6VA	58mm(W)x60mm(D)x93mm(H)	
15VA	80mm(W)x69mm(D)x93mm(H)	


Installation an operation

1. Disconnect power before carrying out any work on the PSD
2. Maximum Wire size 2.5mm² take care not to over tighten the terminal screws.
3. Follow the wiring diagram below. Power supply should be 230Vac

Order Codes:

PSD-1.5	230Vac to 24Vac 1.5VA Power Supply
PSD-6	230Vac to 24Vac 6VA Power Supply
PSD-15	230Vac to 24Vac 15VA Power Supply

Wiring Detail:



EC Products Limited

EC House, Amberley Way, Hounslow,
Middlesex. TW4 6BH. United Kingdom
Tel: +44 (0)20 8569 4100 Fax: +44 (0)20 8569 4111